3 channels 4-20 mA CURRENT RECORDER

Model : MMA-386SD

IA-386SDISO-9001, CE, IEC1010www.yalab.com.tw02-2389-0101

MMA-386SD 4111 2000 Enter Time Power LOG SD Card Data Logger SET **3 CHANNELS** 4-20 mA CURRENT DATA RECORDER







www.YaLAB.com.tw

The Art of Measurement

SD Card real time data logger **3 channels 4-20 mA CURRENT RECORDER** Model : MMA-386SD

FEATURES

* 4-20 mA current loop recorder with real time data logger, save the measuring data along the time information (year, month, date, hour, minute, second) into the SD memory card and can be downloaded to the Excel, extra
software is no need.
* Input signal : 4 to 20 mA, 3 channels.
* Resolution : 0.01 mA.
* Input channels : 3 channels.
* Show 3 channels (CH1, CH2, CH3) 4-20 mA
current loop values in the same LCD.
* Records time and date along with 4-20 mA DC
current measurement value from external sensors,
transducers and many other sources.
* Applications :
4 to 20 mA recording
pH recording
Low level signal monitoring
Photovoltaic studies
Battery studies
Biological sensor monitoring
Factory process control
Research and development
Medical and Pharmaceutical
Environmental studies
* Large LCD display, easy readout.
* Low power consumption and long battery life
when using battery power.
* DC 1.5V (UM-4/AAA) battery x 6 PCs or
optional DC 9V adapter in.
* RS232/USB computer interface.

SPECIFICATIONS

Circuit	Custom one-chip of microprocessor LSI	
	circuit.	Accesso
Display	LCD size : 60 mm x 50 mm	Included
Memory Card	SD memory card. 1 GB to 16 GB.	
Measurement	0 to 20 mA	Optional
Signal		Accesso
CH1, CH2, CH3		
Accuracy	± (0.5% + 0.02 mA)	
Resolution	0.01 mA.	

Datalogger	1/2/5/10/30/60/120/300/600 seconds	
Sampling Time	/Auto	
Data error no.	\leq 0.1 % no. of total saved data typically.	
Advanced	* SD memory card Format	
setting	* Set clock time (Year/Month/Date, Hour/Minute/	
5	Second)	
	* Set sampling time	
	* Set beeper sound ON/OFF	
	* Set SD card Decimal character	
	* Set RS232 data output ON/OFF	
Update Time	Approx. 1 second if measuring data	
of Display	is changed.	
Data Output	RS 232/USB PC computer interface.	
	* Connect the optional RS232 cable	
	UPCB-02 will get the RS232 plug.	
	* Connect the optional USB cable	
	USB-01 will get the USB plug.	
Operating	0 to 50 °C.	
Temperature		
Operating	Less than 85% R.H.	
Humidity		
,		
Power Supply	Alkaline or heavy duty DC 1.5 V battery	
	(UM4, AAA) x 6 PCs, or equivalent.	
	or DC 9V adapter input. (AC/DC power	
	adapter is the optional accessory).	
	* Batteries are also the clock backup	
	power source, so if use AC to DC	
	adapter power supply, it is	
	recommend to install the batteries	
	at any time.	
Weight	199 g/0.44 LB.	
Dimension	132 x 80 x 32 mm	
	(5.2 x 3.1 x 1.3 inch)	
Accessories	* Instruction manual 1 PC	
Included	* Hanging unit (with sticker)1 PC	
	* Wire plug for input socket3 PCs	
Optional	* AC to DC 9V adapter	
Accessories	* SD Card(4 GB)	
	* USB cable, USB-01.	
	* RS232 cable, UPCB-02.	
	* Data Acquisition software, SW-U801-WIN.	
	* Excel Data Acquisition software, SW-E802.	
ect to change wi	thout notice. 1601-MMA386SD	

* Appearance and specifications listed in this brochure are subject www.YaLAB.com.tw 02-2389-0101